

# SSB

## PowerSport

# XR Series

### HIGH PERFORMANCE AGM BATTERY



## DRYCELL

## Australia's Most Powerful AGM Motorcycle Battery Range

**Cover 97% of your battery sales with just 40 XR Series AGM Batteries**

- **Genuine High Performance AGM Battery**
- **Powerful Cranking Power** - Up to 50% more cranking amps than other brands
- **Dry Cell (Non-spillable)** - Don't be fooled by cheap imitations that leak and have no power
- **Extra Long Life**
- **Superior Design & Quality** - Manufactured to Quality Assurance Standard ISO 9001
- **Extreme Vibration Resistant**
- **Can be used on its Side** - Completely sealed and can be used on any angle or side
- **40 Sizes Covers 97% of Sales** - There are over 250 motorcycle battery sizes sold in Australia. 40 XR Series AGM batteries cover 97% of the motorcycle range
- **Suitable for V Twin Motorcycles** - Due to it's high cranking power and it's tough durable design, XR Series batteries can be used in V Twin motorcycles including Harleys
- **Australia's Premium AGM Motorcycle Battery**
- **12 Months National Full Replacement Warranty**
- **When Failure is not an Option** - Use only SSB PowerSport - XR Series

**Super Start Batteries Pty Ltd**  
Head Office

Unit 30 / 76 Hume Highway  
LANSVALE NSW 2166

Tel: (02) 9755 7851 Fax: (02) 9755 7852  
www.superstart.com.au

QUALITY ASSURANCE  
**ISO 9001**





**PowerSport**

# XR Series

## Specifications

MODEL	VOLTS	CCA	AH	LENGTH	WIDTH	HEIGHT	ASSEMBLY FIGURE	WEIGHT (KG)	REGULAR CHARGE	SAME SIZE AS
R6N4-2A	6	-	4	70	70	95	—   —   —   +	0.9	0.4	6N4-2A, 6N4-2A-2, 6N4-2A-3, 6N4-2A-4, 6N4-2A-5, 6N4-2A-7, 6N4-2A-8, 6N4-2A-BS
RB3L-B	12	85	3	98	56	110	—   —   —   —   +	1.2	0.3	CB3L-A, CB3L-B, GB3L-B, YTX3L-BS
RB4L-B	12	105	4	120	70	92	—   —   —   —   +	1.6	0.4	CB4L-A, CB4L-B, GB4L-B, YTX4L-BS
RB5L-B	12	125	5	120	60	130	—   —   —   —   +	1.9	0.5	12N5-3B, CB5L-A, CB5L-B
RB7B-B	12	175	7	146	60	130	+   —   —   —   —   -	2.4	0.7	CB7B-B
RB9-B	12	200	9	135	75	139	+   —   —   —   —   -	3.1	0.9	12N7-4A, 12N7-4B, 12N9-4B-1, CB7-A, CB9-A, CB9-A2, CB9A-A, CB9-B, GB9-B, YT9BA-4, YTX9A-BS
RB9L-B	12	200	9	135	75	139	—   —   —   —   +	3.1	0.9	12N9-3A-1, 12N9-3B, CB9L-B, CB9L-A2, YTX9AL-BS, YT9BAL-4
RB10L-A2	12	235	10	135	90	145	—   —   —   —   +	3.8	1.0	12N10-3A-1, 12N10-3B, 12N11-3A, 12N11-3A-1, 12N11-3B, CB10L-A2, CB10L-B, CB10L-B2, GB10L-A2, YT10L-S
RB12A-A	12	250	12	135	81	161	+   —   —   —   —   -	4.3	1.2	12N12A-4A-1, CB12A-A, CB12A-B, G12N12A-4A-1
RB14A-A2	12	310	12	135	90	167	+   —   —   —   —   -	4.7	1.2	CB14-A1, CB14-A2, CB14A-A1, CB14A-A2, CB14-B2, GB14A-A2, YTX14AH-BS
RB14L-A2	12	310	12	135	90	167	—   —   —   —   +	4.7	1.2	12N14-3A, 12N14-3B, CB14L-A1, CB14L-A2, CB14L-B2, GB14L-A2, YT14AL-S, YTX14AHL-BS
RB16-B	12	385	19	175	100	155	+   —   —   —   —   -	6.5	1.9	12N16-4B, CB16-B, CB16-B-CX, GB16-B, HVT-4
RB16L-B	12	385	19	175	100	155	—   —   —   —   +	6.5	1.9	12N16-3B, CB16-HL-A-CX, CB16L-A2, CB16L-B, GB16L-B, HVT-5
RB16CL-B	12	385	19	175	100	175	—   —   —   —   +	6.6	1.9	CB16CL-B, GB16CL-B, YT16CL-S
RB16AL-A2	12	310	16	205	71	164	—   —   —   —   +	5.7	1.6	CB16AL-A2, GB16AL-A2
R50N18A-A	12	450	21	205	87	162	+   —   —   —   —   -	7.3	2.1	C50N18A-A, YTX24H-BS
R50N18L-A2	12	450	21	205	87	162	—   —   —   —   +	7.3	2.1	12N18-3, 12N18-3A, C50N18L-A2, C50N18L-A-CX, G50N18L-A2, YTX18L-BS, YTX24HL-BS, HVT-6
R60N24-A	12	460	30	165	125	175	+   —   —   —   —   -	9.9	3.0	C60N24-A, 12N24-4
RB30CL-B	12	460	30	165	125	175	—   —   —   —   +	9.9	3.0	CB30CL-B, CB30L-B, 53030, 12N24-3A, C60N24AL-B, C60N24L-A, C60N30AL-B, YIX30L, HVT-2, 12N24-3
R51913	12	320	19	186	81	170	—   —   —   —   +	6.0	1.9	51913, G51913, 51814
RTR4A-BS	12	85	2.3	113	48	85	+   —   —   —   —   -	0.9	0.2	YTR4A-BS
RTX4L-BS	12	105	3	113	70	85	—   —   —   —   +	1.5	0.3	YTX4L-BS, GTX4L-BS, YTZ5-S
RTX5L-BS	12	195	6	113	70	105	—   —   —   —   +	2.1	0.6	YTX5L-BS, YTZ7-S, GTZ7-S, YTZ7-S-BS
RTX7A-BS	12	150	6	150	87	93	+   —   —   —   —   -	2.5	0.6	YTX7A-BS
RTX7L-BS	12	175	6	113	70	130	—   —   —   —   +	2.4	0.6	YTX7L-BS, GTX7L-BS, YTZ7A-S
RTX9-BS	12	260	10	150	87	105	+   —   —   —   —   -	3.4	1.0	YTX9-BS, YTR9-BS, GTX9-BS, YTX12A-BS
RTX12-BS	12	265	10	150	87	130	+   —   —   —   —   -	3.9	1.0	GTX12-BS, YT12BA-4, YTX12-BS
RTX14-BS	12	290	12	150	87	145	+   —   —   —   —   -	4.5	1.2	GTX14-BS, YT14BA-4, YTX14-BS, HVT-8
RTX14L-BS	12	290	12	150	87	145	—   —   —   —   +	4.5	1.2	YTX14L-BS, HVT-3
RTX15L-BS	12	340	13	175	87	130	—   —   —   —   +	4.7	1.3	YTX15L-BS
RTX16-BS	12	340	14	150	87	161	+   —   —   —   —   -	5.1	1.4	YTX16-BS, YTX16H-BS
RTX20-BS	12	400	18	175	87	155	+   —   —   —   —   -	5.9	1.8	YTX20-BS, YTX20H-BS
RTX20L-BS	12	400	18	175	87	155	—   —   —   —   +	5.9	1.8	YTX20L-BS, YTX20HL-BS, GTX20L-BS, YIX20L, HVT-1
RT4B-4	12	85	2.3	113	38	85	+   —   —   —   —   -	0.9	0.2	YT4B-4
RT6.5B-3	12	130	6.5	139	66	102	—   —   —   —   +	2.3	0.6	YT6.5B-3
RT7B-4	12	150	6.5	150	65	93	+   —   —   —   —   -	2.3	0.6	YT7B-4, YT7B-4-BS
RT9B-4	12	200	8	150	68	105	+   —   —   —   —   -	2.7	0.8	YT9B-4, YT9B-4-BS
RTZ10-S	12	280	8.6	150	87	93	+   —   —   —   —   -	2.9	0.8	YTZ10-S, GTZ10-S, YTZ10-S-BS
RT12B-4	12	260	10	150	69	130	+   —   —   —   —   -	3.6	1.0	GT12B-4, YT12B-4, YT12B-4-BS
RT14B-4	12	310	12	150	69	145	+   —   —   —   —   -	4.1	1.2	YT14B-4, YT14B-4-BS
RTZ14-S	12	340	11.2	150	87	110	+   —   —   —   —   -	3.6	1.1	YTZ14-S, GTZ14-S, YTZ14-S-BS, YTZ12-S